

DATA SHEET

PAG MPL USB-C Output Unit

PAG-6002 / EAN 5060845320537

- Output unit for powering personal devices, such as phones, from Mini PAGlink batteries.
- Suitable for powering 5V, 9V and 12V devices.
- 1 x USB-C PD output 3A, 36W.
- Quick and easy to fit.
- Interchangeable with other output units for Mini PAGlink batteries.

This USB type C output unit increases the range of devices that can be powered using your already versatile Mini PAGlink batteries.

It outputs 3A at 5V, 9V and 12V, enabling a total of 36W to be drawn. The output voltage is determined automatically by the device that you connect. It is compatible with most phones and can be used to power low-voltage camera accessories.

The unit plugs into the output port in place of the USB-A unit supplied with every Mini PAGlink battery.



Output units can be released from the Mini PAGlink battery output port using the slider situated on the rear of the battery. Other output units that feature a D-Tap, Lemo (2-pin), Hirose (4-pin) and 2.1 - 2.5mm connector can also be used in place of the USB.

This type C output unit will charge a laptop battery but cannot be used to power a laptop.



SPECIFICATION

Model No. PAG-6002

Input Connection:

Input voltage: 12-24V. To be powered via the output port of Mini PAGlink batteries.

USB-C Output (PD Fast-Charge):

Maximum 36W. 5V-3A, 9V-3A, 12V-3A, device selected.

Suitable Batteries:

Mini PAGlink (V-Mount or Gold Mount).

Warranty:

2 years.

© PAG Ltd. PAG is the trademark of PAG Ltd. / PAG reserves the right to change the specifications contained herein without notice.



PAG Ltd. UK
Epsom Downs Metro Centre
Units 9 & 10, Waterfield,
Tadworth, Surrey KT20 5LR

E sales@paguk.com
T +44 (0)20 8543 3131
www.paguk.com