

DATA SHEET

Gold Mount Plate for Alexa 35

PAG-7004 / EAN 5060845320575

- Gold Mount battery connector plate designed to replace the B-Mount plate supplied with the Arri Alexa 35.
- Features PAG's Cinergy barcode, positioned precisely for alignment with the sensor on the rear of the Mini PAGlink Cinergy Battery. This enables the voltage output of two 14V batteries to be combined to provide 28V.
- High-current contact pins.

PAG's Gold Mount plate for the Arri Alexa 35 camera is a durable battery mount that features high-current contact pins and a sprung lever for battery removal.

The plate is easy to fit, requiring only the screws provided.

PAG has applied the Cinergy barcode label to this Gold Mount plate so that the Gold Mount Cinergy battery system can be used to power the Arri Alexa 35. When you link a PAG MPL99 Cinergy battery to another PAG MPL99 battery, and connect it to this mount, the Cinergy battery's



sensor will read the barcode and initiate high-voltage mode, when the Cinergy battery's display button is pressed for 3 seconds. The voltage output of both 14V batteries will be combined.



Cinergy
Barcode
Label

Cinergy
Sensor

Standard
MPL99

SPECIFICATION

Model No. PAG-7004

Dimensions:

Length:	118mm	4.6"
Width:	93mm	3.6"
Depth:	23mm	0.9"

Suitable Batteries:

Gold Mount.

Warranty:

2 years.

© PAG Ltd. PAG is the trademark of PAG Ltd. / PAG reserves the right to change the specifications contained herein without notice.



PAG Ltd. UK
Epsom Downs Metro Centre
Units 9 & 10, Waterfield,
Tadworth, Surrey KT20 5LR

E sales@paguk.com
T +44 (0)20 8543 3131
www.paguk.com